



## METHOD AND DEVICE FOR ROBUST PATTERN RECOGNITION

### TECHNICAL FIELD

The present invention relates to recognition of a scanned signal pattern subjected to disruptions.

### BACKGROUND ART

10 Scanning methods are widely used in many disciplines to convert dimensional patterns to time, or temporal, functions. Examples include X-rays, Computer-Aided-Tomography (CAT), forensics, TV imaging devices, spectrometry, chromatography; SONAR, RADAR, and many other systems. A pattern recognizer's task is to detect and identify entities revealed by energy perturbations encountered during a scan. Signatures of interest often exhibit interfering and changing temporal patterns. Amplitudes may arbitrarily change. Interception strengths may change with radiation conditions, substance concentrations, collection methods, equipment artifacts, etc. Signature components may disappear  
20 completely when a signal becomes weak. Disruptive components from extraneous sources may arise, and many other variations may occur. Accordingly, current recognition devices commonly require high signal-to-background ratios to reliably recognize patterns.

Pattern research usually treats a pattern as a set of points,

or 'descriptors', in dimensioned space. Patterns are assigned to a class when some sort of mean-square distance between the pattern's descriptors and those of a specific template falls sufficiently below similar distances to other templates. An advantage to the approach is that it has a well-established mathematical foundation. In all but specialized or highly simplified cases, however, pattern descriptors in signals may appear or disappear. Locations frequently will be indefinite. Space dimensionality can change in unpredictable manners. Static analytical methods are limited.

When attempting to identify a changeable pattern, the recognition process cannot be restricted to a simple template-matching procedure. A human, for example, has been conditioned to subconsciously grade available cues such as spatial ratios, colors, etc., in comparing an image to one in memory. Cues most important to proper recognition are emphasized. Aspect angles can vary widely, and there is no exact measuring rod in the brain. In a recognition process, as opposed to observation, sensory cues assume dynamically varying degrees of importance, or weights. A decision is based upon the 'comfort' with which an emerging set of cues resembles a set in memory. Recognition rules themselves thus dynamically vary, and are affected by factors not intrinsically contained in a pattern.

Current art most often employs a well-ordered pattern space,

usually of two dimensions. Boolean rules typically are applied to quantized regions in that space. Speech recognition, for example, frequently uses zones of frequency and time. Character recognition uses quantized Cartesian coordinates. Such methods are vulnerable to entropy in the form of noise disruptions or spatial distortions.

#### SUMMARY OF THE INVENTION

10 Template Generation The present invention modifies templates representing entities to be recognized. Modifications result in more robust recognition in the presence of noise and other disruptions. A pattern to be recognized is scanned to produce a temporal function. If essentially continuous, the function is transformed by a selected mathematical process to produce favorable types and numbers of descriptors. Each descriptor, typically in the form of a number, defines a temporal event such as a relative time and direction of a zero crossing. A group of descriptors derived from an entity-produced pattern is stored as an initial template. Similar processes provide initial templates for each entity of interest.

20

Once a set of initial templates has been established, the entire set is subjected to a unique group edit that seeks cross-correlations among all paired combinations. Degrees of cross-correlation are scored. The pair exhibiting a highest score is considered the most likely to produce a recognition error, and is

selected for revisions.

Descriptors that can improve recognition accuracies are found and attached to appropriate templates. Each time a revision has occurred, the revised template is substituted for the old, and the search-and-revise sequence repeated. If no further improvement is possible, the user is informed, and the edit discontinued. Otherwise the edit process continues until all scores fall below a preset threshold. Each final template has been influenced by all other templates.

Pattern Processing Intercepted-signal patterns to be recognized are transformed to produce descriptors in the manner used to create initial templates, but are not subjected to the template-modification process. A recognition decision conforms to the highest degree of match, or score, produced by comparison to an edited template. A score is derived in the current invention as follows:

A first descriptor of a first edited-template is compared to every signal descriptor in a template-to-signal one-many correspondence. If a match occurs, a score is increased. If no match is found, the score is decreased.

A similar procedure is followed for each edited-template

descriptor. If, for example, there are fourteen template descriptors and sixteen signal descriptors, a total of  $14 \times 16$ , or 224 descriptor-match attempts are made. The template-to-signal many-one process has the unique property of accommodating length and/or descriptor-order changes in a signal pattern corrupted by spurious pulses.

10 If the number of descriptors in a particular template had been increased by the edit process, the number of descriptor match-attempts would increase for that template. The scores of proper recognitions rise (more matches), and those of improper recognitions drop (more errors). Thus the one-many descriptor comparison process combined with group edit increases auto-correlation (proper recognition) scores, lowers cross-correlation (improper recognition) scores, and greatly improves noise immunity. The edit causes measurement criteria to differ among patterns.

20 It is therefore an object of the present invention to provide a method of generating improved descriptor sets for scanned patterns.

Another object of the invention is to provide a method of generating a recognition rule peculiar to a pattern class.

Another object of the invention is to provide a one-many descriptor

comparison procedure between a template and signal to reduce effects of noise disruptions.

Another object of the invention is to provide a method and apparatus for editing a group of templates to increase auto-correlations and decrease cross-correlations among patterns.

Yet another object of the invention is to provide a method and apparatus for controlling the significance of a selected descriptor within a pattern cipher.

Still another object of the invention is to provide a method and apparatus for scoring a degree of match between a pair of templates.

Yet another object of the invention is to provide a method and apparatus for pattern recognition that is robust under noise disruptions.

## 20 BRIEF DESCRIPTION OF THE DRAWINGS

The features and advantages of the present invention will be more clearly understood when the detailed description of a preferred embodiment described below is considered in conjunction with the drawings provided in which:

FIG. 1 is a block diagram of apparatus for recognizing a pattern in accordance with the present invention;

FIG. 2 is a representation of a typical temporal scan of an entity showing zero-crossing descriptor points in accordance with the present invention;

FIG. 3 is a cipher produced by the waveform of FIG. 2;

FIG. 4 is the cipher of FIG. 3 paired with another cipher demonstrating descriptor cross-correlations;

FIG. 5 represents the ciphers of FIG.3 converted to templates after a group edit; and

FIG. 6 is the waveform of FIG. 2 showing the effect of a noise pulse.

#### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Referring to the block diagram of FIG. 1, SCANNER 1 is a generic scanning stage representing those found in many existing systems. The function of SCANNER 1 is to convert energy functions derived from entities such as distance-related terrain features, chemical substances, boats or aircraft, electromagnetic signals, sounds, etc., into electrical temporal functions. Examples abound. TV raster scans, RADAR, SONAR, X-ray imaging, spectrometers, seismic sensors, and many other applications produce such energy functions. In most cases an entity reflects, refracts, absorbs, or otherwise modulates, energy from an irradiating source such as sunlight, sound, heat, electromagnetic radiation, etc., to produce

its identifying energy function.

SCANNER 1 is driven by COLLECTION TIMER 2 which assures that WAVEFORM PROCESSOR 3 and DESCRIPTOR GENERATOR 4 are synchronized with each scan. Timing connections are shown dashed in the figure. The scanned function can thereby be resolved into a number of measurable time intervals, or cells, as shown in FIG. 2.

10 WAVEFORM PROCESSOR 3 will produce an undulating waveform 22 corresponding to an energy function of a scanned entity. Waveforms in a preferred embodiment of the invention have shapes that will produce numerous zero-axis crossings. Circuits in PROCESSOR 3 are selected to produce stable zero-axis crossings such as 18 and 19. Each crossing's direction and location is a 'descriptor' of the pattern produced by the scan. Circuits in PROCESSOR 3 may range from simple amplifiers to orthogonal-series expandors, frequency-selective elements, differentiators, or other transformation devices to provide a suitable number of descriptors. Details of various transformations are well-known and fully described in the literature. Once a transformation is selected, it must be consistently applied in the invention.

Referring to FIG. 2, a scan duration is divided into identifiable cells. For expository purposes, they are given alphabetical labels. A symbol such as the numeral one is attached



to a descriptor label to indicate direction of crossing. In the example, the numeral indicates a plus-to-minus crossing. Under such rules, descriptors for the waveform of FIG. 2 are shown in FIG. 3. Such an entire group will be called a "cipher" hereafter. It is clear that other symbols such as hexadecimal or binary notations could also have been used to create ciphers.

10  
20  
30  
40  
50  
60  
70  
80  
90  
100  
110  
120  
130  
140  
150  
160  
170  
180  
190  
200  
210  
220  
230  
240  
250  
260  
270  
280  
290  
300  
310  
320  
330  
340  
350  
360  
370  
380  
390  
400  
410  
420  
430  
440  
450  
460  
470  
480  
490  
500  
510  
520  
530  
540  
550  
560  
570  
580  
590  
600  
610  
620  
630  
640  
650  
660  
670  
680  
690  
700  
710  
720  
730  
740  
750  
760  
770  
780  
790  
800  
810  
820  
830  
840  
850  
860  
870  
880  
890  
900  
910  
920  
930  
940  
950  
960  
970  
980  
990  
1000  
1010  
1020  
1030  
1040  
1050  
1060  
1070  
1080  
1090  
1100  
1110  
1120  
1130  
1140  
1150  
1160  
1170  
1180  
1190  
1200  
1210  
1220  
1230  
1240  
1250  
1260  
1270  
1280  
1290  
1300  
1310  
1320  
1330  
1340  
1350  
1360  
1370  
1380  
1390  
1400  
1410  
1420  
1430  
1440  
1450  
1460  
1470  
1480  
1490  
1500  
1510  
1520  
1530  
1540  
1550  
1560  
1570  
1580  
1590  
1600  
1610  
1620  
1630  
1640  
1650  
1660  
1670  
1680  
1690  
1700  
1710  
1720  
1730  
1740  
1750  
1760  
1770  
1780  
1790  
1800  
1810  
1820  
1830  
1840  
1850  
1860  
1870  
1880  
1890  
1900  
1910  
1920  
1930  
1940  
1950  
1960  
1970  
1980  
1990  
2000  
2010  
2020  
2030  
2040  
2050  
2060  
2070  
2080  
2090  
2100  
2110  
2120  
2130  
2140  
2150  
2160  
2170  
2180  
2190  
2200  
2210  
2220  
2230  
2240  
2250  
2260  
2270  
2280  
2290  
2300  
2310  
2320  
2330  
2340  
2350  
2360  
2370  
2380  
2390  
2400  
2410  
2420  
2430  
2440  
2450  
2460  
2470  
2480  
2490  
2500  
2510  
2520  
2530  
2540  
2550  
2560  
2570  
2580  
2590  
2600  
2610  
2620  
2630  
2640  
2650  
2660  
2670  
2680  
2690  
2700  
2710  
2720  
2730  
2740  
2750  
2760  
2770  
2780  
2790  
2800  
2810  
2820  
2830  
2840  
2850  
2860  
2870  
2880  
2890  
2900  
2910  
2920  
2930  
2940  
2950  
2960  
2970  
2980  
2990  
3000  
3010  
3020  
3030  
3040  
3050  
3060  
3070  
3080  
3090  
3100  
3110  
3120  
3130  
3140  
3150  
3160  
3170  
3180  
3190  
3200  
3210  
3220  
3230  
3240  
3250  
3260  
3270  
3280  
3290  
3300  
3310  
3320  
3330  
3340  
3350  
3360  
3370  
3380  
3390  
3400  
3410  
3420  
3430  
3440  
3450  
3460  
3470  
3480  
3490  
3500  
3510  
3520  
3530  
3540  
3550  
3560  
3570  
3580  
3590  
3600  
3610  
3620  
3630  
3640  
3650  
3660  
3670  
3680  
3690  
3700  
3710  
3720  
3730  
3740  
3750  
3760  
3770  
3780  
3790  
3800  
3810  
3820  
3830  
3840  
3850  
3860  
3870  
3880  
3890  
3900  
3910  
3920  
3930  
3940  
3950  
3960  
3970  
3980  
3990  
4000  
4010  
4020  
4030  
4040  
4050  
4060  
4070  
4080  
4090  
4100  
4110  
4120  
4130  
4140  
4150  
4160  
4170  
4180  
4190  
4200  
4210  
4220  
4230  
4240  
4250  
4260  
4270  
4280  
4290  
4300  
4310  
4320  
4330  
4340  
4350  
4360  
4370  
4380  
4390  
4400  
4410  
4420  
4430  
4440  
4450  
4460  
4470  
4480  
4490  
4500  
4510  
4520  
4530  
4540  
4550  
4560  
4570  
4580  
4590  
4600  
4610  
4620  
4630  
4640  
4650  
4660  
4670  
4680  
4690  
4700  
4710  
4720  
4730  
4740  
4750  
4760  
4770  
4780  
4790  
4800  
4810  
4820  
4830  
4840  
4850  
4860  
4870  
4880  
4890  
4900  
4910  
4920  
4930  
4940  
4950  
4960  
4970  
4980  
4990  
5000  
5010  
5020  
5030  
5040  
5050  
5060  
5070  
5080  
5090  
5100  
5110  
5120  
5130  
5140  
5150  
5160  
5170  
5180  
5190  
5200  
5210  
5220  
5230  
5240  
5250  
5260  
5270  
5280  
5290  
5300  
5310  
5320  
5330  
5340  
5350  
5360  
5370  
5380  
5390  
5400  
5410  
5420  
5430  
5440  
5450  
5460  
5470  
5480  
5490  
5500  
5510  
5520  
5530  
5540  
5550  
5560  
5570  
5580  
5590  
5600  
5610  
5620  
5630  
5640  
5650  
5660  
5670  
5680  
5690  
5700  
5710  
5720  
5730  
5740  
5750  
5760  
5770  
5780  
5790  
5800  
5810  
5820  
5830  
5840  
5850  
5860  
5870  
5880  
5890  
5900  
5910  
5920  
5930  
5940  
5950  
5960  
5970  
5980  
5990  
6000  
6010  
6020  
6030  
6040  
6050  
6060  
6070  
6080  
6090  
6100  
6110  
6120  
6130  
6140  
6150  
6160  
6170  
6180  
6190  
6200  
6210  
6220  
6230  
6240  
6250  
6260  
6270  
6280  
6290  
6300  
6310  
6320  
6330  
6340  
6350  
6360  
6370  
6380  
6390  
6400  
6410  
6420  
6430  
6440  
6450  
6460  
6470  
6480  
6490  
6500  
6510  
6520  
6530  
6540  
6550  
6560  
6570  
6580  
6590  
6600  
6610  
6620  
6630  
6640  
6650  
6660  
6670  
6680  
6690  
6700  
6710  
6720  
6730  
6740  
6750  
6760  
6770  
6780  
6790  
6800  
6810  
6820  
6830  
6840  
6850  
6860  
6870  
6880  
6890  
6900  
6910  
6920  
6930  
6940  
6950  
6960  
6970  
6980  
6990  
7000  
7010  
7020  
7030  
7040  
7050  
7060  
7070  
7080  
7090  
7100  
7110  
7120  
7130  
7140  
7150  
7160  
7170  
7180  
7190  
7200  
7210  
7220  
7230  
7240  
7250  
7260  
7270  
7280  
7290  
7300  
7310  
7320  
7330  
7340  
7350  
7360  
7370  
7380  
7390  
7400  
7410  
7420  
7430  
7440  
7450  
7460  
7470  
7480  
7490  
7500  
7510  
7520  
7530  
7540  
7550  
7560  
7570  
7580  
7590  
7600  
7610  
7620  
7630  
7640  
7650  
7660  
7670  
7680  
7690  
7700  
7710  
7720  
7730  
7740  
7750  
7760  
7770  
7780  
7790  
7800  
7810  
7820  
7830  
7840  
7850  
7860  
7870  
7880  
7890  
7900  
7910  
7920  
7930  
7940  
7950  
7960  
7970  
7980  
7990  
8000  
8010  
8020  
8030  
8040  
8050  
8060  
8070  
8080  
8090  
8100  
8110  
8120  
8130  
8140  
8150  
8160  
8170  
8180  
8190  
8200  
8210  
8220  
8230  
8240  
8250  
8260  
8270  
8280  
8290  
8300  
8310  
8320  
8330  
8340  
8350  
8360  
8370  
8380  
8390  
8400  
8410  
8420  
8430  
8440  
8450  
8460  
8470  
8480  
8490  
8500  
8510  
8520  
8530  
8540  
8550  
8560  
8570  
8580  
8590  
8600  
8610  
8620  
8630  
8640  
8650  
8660  
8670  
8680  
8690  
8700  
8710  
8720  
8730  
8740  
8750  
8760  
8770  
8780  
8790  
8800  
8810  
8820  
8830  
8840  
8850  
8860  
8870  
8880  
8890  
8900  
8910  
8920  
8930  
8940  
8950  
8960  
8970  
8980  
8990  
9000  
9010  
9020  
9030  
9040  
9050  
9060  
9070  
9080  
9090  
9100  
9110  
9120  
9130  
9140  
9150  
9160  
9170  
9180  
9190  
9200  
9210  
9220  
9230  
9240  
9250  
9260  
9270  
9280  
9290  
9300  
9310  
9320  
9330  
9340  
9350  
9360  
9370  
9380  
9390  
9400  
9410  
9420  
9430  
9440  
9450  
9460  
9470  
9480  
9490  
9500  
9510  
9520  
9530  
9540  
9550  
9560  
9570  
9580  
9590  
9600  
9610  
9620  
9630  
9640  
9650  
9660  
9670  
9680  
9690  
9700  
9710  
9720  
9730  
9740  
9750  
9760  
9770  
9780  
9790  
9800  
9810  
9820  
9830  
9840  
9850  
9860  
9870  
9880  
9890  
9900  
9910  
9920  
9930  
9940  
9950  
9960  
9970  
9980  
9990  
10000  
10010  
10020  
10030  
10040  
10050  
10060  
10070  
10080  
10090  
10100  
10110  
10120  
10130  
10140  
10150  
10160  
10170  
10180  
10190  
10200  
10210  
10220  
10230  
10240  
10250  
10260  
10270  
10280  
10290  
10300  
10310  
10320  
10330  
10340  
10350  
10360  
10370  
10380  
10390  
10400  
10410  
10420  
10430  
10440  
10450  
10460  
10470  
10480  
10490  
10500  
10510  
10520  
10530  
10540  
10550  
10560  
10570  
10580  
10590  
10600  
10610  
10620  
10630  
10640  
10650  
10660  
10670  
10680  
10690  
10700  
10710  
10720  
10730  
10740  
10750  
10760  
10770  
10780  
10790  
10800  
10810  
10820  
10830  
10840  
10850  
10860  
10870  
10880  
10890  
10900  
10910  
10920  
10930  
10940  
10950  
10960  
10970  
10980  
10990  
11000  
11010  
11020  
11030  
11040  
11050  
11060  
11070  
11080  
11090  
11100  
11110  
11120  
11130  
11140  
11150  
11160  
11170  
11180  
11190  
11200  
11210  
11220  
11230  
11240  
11250  
11260  
11270  
11280  
11290  
11300  
11310  
11320  
11330  
11340  
11350  
11360  
11370  
11380  
11390  
11400  
11410  
11420  
11430  
11440  
11450  
11460  
11470  
11480  
11490  
11500  
11510  
11520  
11530  
11540  
11550  
11560  
11570  
11580  
11590  
11600  
11610  
11620  
11630  
11640  
11650  
11660  
11670  
11680  
11690  
11700  
11710  
11720  
11730  
11740  
11750  
11760  
11770  
11780  
11790  
11800  
11810  
11820  
11830  
11840  
11850  
11860  
11870  
11880  
11890  
11900  
11910  
11920  
11930  
11940  
11950  
11960  
11970  
11980  
11990  
12000  
12010  
12020  
12030  
12040  
12050  
12060  
12070  
12080  
12090  
12100  
12110  
12120  
12130  
12140  
12150  
12160  
12170  
12180  
12190  
12200  
12210  
12220  
12230  
12240  
12250  
12260  
12270  
12280  
12290  
12300  
12310  
12320  
12330  
12340  
12350  
12360  
12370  
12380  
12390  
12400  
12410  
12420  
12430  
12440  
12450  
12460  
12470  
12480  
12490  
12500  
12510  
12520  
12530  
12540  
12550  
12560  
12570  
12580  
12590  
12600  
12610  
12620  
12630  
12640  
12650  
12660  
12670  
12680  
12690  
12700  
12710  
12720  
12730  
12740  
12750  
12760  
12770  
12780  
12790  
12800  
12810  
12820  
12830  
12840  
12850  
12860  
12870  
12880  
12890  
12900  
12910  
12920  
12930  
12940  
12950  
12960  
12970  
12980  
12990  
13000  
13010  
13020  
13030  
13040  
13050  
13060  
13070  
13080  
13090  
13100  
13110  
13120  
13130  
13140  
13150  
13160  
13170  
13180  
13190  
13200  
13210  
13220  
13230  
13240  
13250  
13260  
13270  
13280  
13290  
13300  
13310  
13320  
13330  
13340  
13350  
13360  
13370  
13380  
13390  
13400  
13410  
13420  
13430  
13440  
13450  
13460  
13470  
13480  
13490  
13500  
13510  
13520  
13530  
13540  
13550  
13560  
13570  
13580  
13590  
13600  
13610  
13620  
13630  
13640  
13650  
13660  
13670  
13680  
13690  
13700  
13710  
13720  
13730  
13740  
13750  
13760  
13770  
13780  
13790  
13800  
13810  
13820  
13830  
13840  
13850  
13860  
13870  
13880  
13890  
13900  
13910  
13920  
13930  
13940  
13950  
13960  
13970  
13980  
13990  
14000  
14010  
14020  
14030  
14040  
14050  
14060  
14070  
14080  
14090  
14100  
14110  
14120  
14130  
14140  
14150  
14160  
14170  
14180  
14190  
14200  
14210  
14220  
14230  
14240  
14250  
14260  
14270  
14280  
14290  
14300  
14310  
14320  
14330  
14340  
14350  
14360  
14370  
14380  
14390  
14400  
14410  
14420  
14430  
14440  
14450  
14460  
14470  
14480  
14490  
14500  
14510  
14520  
14530  
14540  
14550  
14560  
14570  
14580  
14590  
14600  
14610  
14620  
14630  
14640  
14650  
14660  
14670  
14680  
14690  
14700  
14710  
14720  
14730  
14740  
14750  
14760  
14770  
14780  
14790  
14800  
14810  
14820  
14830  
14840  
14850  
14860  
14870  
14880  
14890  
14900  
14910  
14920  
14930  
14940  
14950  
14960  
14970  
14980  
14990  
15000  
15010  
15020  
15030  
15040  
15050  
15060  
15070  
15080  
15090  
15100  
15110  
15120  
15130  
15140  
15150  
15160  
15170  
15180  
15190  
15200  
15210  
15220  
15230  
15240  
15250  
15260  
15270  
15280  
15290  
15300  
15310  
15320  
15330  
15340  
15350  
15360  
15370  
15380  
15390  
15400  
15410  
15420  
15430  
15440  
15450  
15460  
15470  
15480  
15490  
15500  
15510  
15520  
15530  
15540  
15550  
15560  
15570  
15580  
15590  
15600  
15610  
15620  
15630  
15640  
15650  
15660  
15670  
15680  
15690  
15700  
15710  
15720  
15730  
15740  
15750  
15760  
15770  
15780  
15790  
15800  
15810  
15820  
15830  
15840  
15850  
15860  
15870  
15880  
15890  
15900  
15910  
15920  
15930  
15940  
15950  
15960  
15970  
15980  
15990  
16000  
16010  
16020  
16030  
16040  
16050  
16060  
16070  
16080  
16090  
16100  
16110  
16120  
16130  
16140  
16150  
16160  
16170  
16180  
16190  
16200  
16210  
16220  
16230  
16240  
16250  
16260  
16270  
16280  
16290  
16300  
16310  
16320  
16330  
16340  
16350  
16360  
16370  
16380  
16390  
16400  
16410  
16420  
16430  
16440  
16450  
16460  
16470  
16480  
16490  
16500  
16510  
16520  
16530  
16540  
16550  
16560  
16570  
16580  
16590  
16600  
16610  
16620  
16630  
16640  
16650  
16660  
16670  
16680  
16690  
16700  
16710  
16720  
16730  
16740  
16750  
16760  
16770  
16780  
16790  
16800  
16810  
16820  
16830  
16840  
16850  
16860  
16870  
16880  
16890  
16900  
16910  
16920  
16930  
16940  
16950  
16960  
16970  
16980  
16990  
17000  
17010  
17020  
17030  
17040  
17050  
17060  
17070  
17080  
17090  
17100  
17110  
17120  
17130  
17140  
17150  
17160  
17170  
17180  
17190  
17200  
17210  
17220  
17230  
17240  
17250  
17260  
17270  
17280  
17290  
17300  
17310  
17320  
17330  
17340  
17350  
17360  
17370  
17380  
17390  
17400  
17410  
17420  
17430  
17440  
17450  
17460  
17470  
17480  
17490  
17500  
17510  
17520  
17530  
17540  
17550  
17560  
17570  
17580  
17590  
17600  
17610  
17620  
17630  
17640  
17650  
17660  
17670  
17680  
17690  
17700  
17710  
17720  
17730  
17740  
17750  
17760  
17770  
17780  
17790  
17800  
17810  
17820  
17830  
17840  
17850  
17860  
17870  
17880  
17890  
17900  
17910  
17920  
17930  
17940  
17950  
17960  
17970  
17980  
17990  
18000  
18010  
18020  
18030  
18040  
18050  
18060  
18070  
18080  
18090  
18100  
18110  
18120  
18130  
18140  
18150  
18160  
18170  
18180  
18190  
18200  
18210  
18220  
18230  
18240  
18250  
18260  
18270  
18280  
18290  
18300  
18310  
18320  
18330  
18340  
18350  
18360  
18370  
18380  
18390  
18400  
18410  
18420  
18430  
18440  
18450  
18460  
18470  
18480  
18490  
18500  
18510  
18520  
18530  
18540  
18550  
18560  
18570  
18580  
18590  
18600  
18610  
18620  
18630  
18640  
18650  
18660  
18670  
18680  
18690  
18700  
18710  
18720  
18730  
18740  
18750  
18760  
18770  
18780  
18790  
18800  
18810  
18820  
18830  
18840  
18850  
18860  
18870  
18880  
18890  
18900  
18910  
18920  
18930  
18940  
18950  
18960  
18970  
18980  
18990  
19000  
19010  
19020  
19030  
19040  
19050  
19060  
19070  
1908

purposes, if a template descriptor and a signal descriptor of an entity match, they will be assumed to increase the recognition score for that entity by one. If not, they will be assumed to decrease the score by one. Accordingly, if all eight descriptors of FIG. 3 were compared to a completely matching template, an entity score of eight would result. A single mismatch would drop the score to seven minus one, or six.

10 An entity different from the one producing FIG. 3 may produce one or more descriptors that match those of FIG. 3. Assume, for example, that the waveform of FIG. 2 were derived from a spectral scan of an aqueous solution of a substance to be recognized. If an aqueous solution of a different substance were to be separately recognized, its waveform would likely produce water-produced descriptors that would match some in FIG. 3. If water itself were to be recognized, all of its descriptors could possibly fall into the FIG. 3 cipher. An overlapping, or cross-correlation, situation is depicted in FIG. 4 where matched descriptors are shaded.

20 Assume that switch 6 of FIG. 1 had been closed to store the cipher of FIG. 3 as upper cipher 10 of FIG. 4. Cipher 10 then is an initial template representing the waveform of FIG. 2. If each of the six descriptors in lower cipher 11 were compared to a sequence of all eight upper cipher 10 descriptors, five would find a match. A score of five minus one, or four, would result. If, on

the other hand, upper cipher 10 were a signal pattern and lower cipher 11 a template, a similar comparison process would produce three mismatches and a score of five minus three, or two. Cross-correlations thus do not always commute under the rules. A to B is not necessarily the same as B to A, primarily because the number of descriptors can differ. Employing a descriptor sum as a recognition cue is dangerous in most cases because noise pulses can easily change it.

10        Templates are usually generated under controlled conditions. They are relatively noise-free. In contrast, signal patterns often vary greatly in length and strength. They are frequently corrupted by noise pulses and missing descriptors. The recognition procedure of the invention acknowledges that unbalance, and exploits superior template stability to greatly reduce noise effects.

20        The invention selects a one-many correspondence from template to signal to improve recognition capabilities. Thus, a first template descriptor is compared to all signal descriptors, a second template descriptor is compared to all signal descriptors, etc. If the signal has been corrupted by the addition of noise pulses or is missing weak descriptors, any disorder in its sequence becomes irrelevant. The process continues until all template descriptors have been able to seek a match. If non-matching noise pulses are encountered in the process, they are ignored (with no penalty). On

the other hand, if a template descriptor fails to find its match anywhere in a signal descriptor set, the score is lowered.

10 An example is shown in FIG. 5. The Figure is identical to FIG. 4, except that a pair of noise-produced zero-crossings 12,13 have been inserted into cipher 14, representing a disrupted signal cipher of FIG. 3. When lower cipher 11 (a template) is tested in a one-many correspondence to cipher 14, the score is five minus one, or four. The score is exactly the same as in the corresponding uncorrupted case of FIG. 4. Signal length change and noise content were ignored.

DESCRIPTOR COMPARATOR 17 of FIG. 1 provides the described template-to-signal, one-to-many correspondence. A reverse procedure will not work. In that case a noise pulse in the signal would be treated as a true descriptor. When unable to find a match anywhere in the template, the pulse would trigger a penalty. Noise pulses would incorrectly affect scores.

20 Discussions relative to FIG's 4 and 5 emphasized the necessity of always designating a 'template' cipher and a 'signal' cipher. Their roles can be reversed for special purposes. That procedure is exploited in the present invention to greatly reduce incidences of improper recognitions.

10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20

Referring to FIG. 1, a group of initial templates can be obtained from entity scans by closing switch 6 and transferring them to TEMPLATE STORAGE 7. It is obvious to those skilled in the art that such templates can alternatively be placed in archival files and retrieved when desired. Once a set of initial templates has been placed into STORAGE 7, the entire set can be subjected to a unique group edit by closing switch 15 and activating GROUP EDIT 16. EDIT 16 generates a series of template-to-template comparisons. The non-commutating nature of cross-correlations means that if N entities are in a population,  $N(N-1)$  possible entity pairings (excluding identities) can occur. For example, if ten entities are involved, ninety possible cross-correlations can occur.

EDIT 16 subjects every pair of templates in the set to cross-correlation tests in which one member is treated as a template and the other as a 'signal'. Scores are found in the manner described relative to FIG. 4. The pair exhibiting a highest score is considered the most likely to produce a recognition error, and is selected for revisions.

Assume that the cipher pair of FIG. 4 comprises a pair of templates and has been selected because its cross-correlation score from 'signal' 11 to 'template' 10 was four. 'Template' member 10 of the pair is first examined to find if it has a descriptor that

does not appear in 'signal' member 11. In FIG. 5, descriptors 23, 27, and 28 are found. Any of the three could be selected, but assume that descriptor 23 is chosen. Descriptor 23 is then enhanced, preferably by simply repeating it as descriptor 25 shown in FIG. 6. Descriptor 25 in 'template' 10' is, like descriptor 23, unable to find a match in 'signal' 11'. The score is therefore reduced by one. 'Template' and 'signal' roles can then be reversed and a similar test applied.

10 If no disjunct descriptors had been found in either case, the templates would have been identical. No pattern separation would be possible for the pair. The user would be informed.

In the example of FIG. 6, descriptor 23 was found and enhanced by inserting it again as descriptor 25. Upon a reversal test, descriptor 24 was enhanced by inserting descriptor 26. The ciphers of FIG. 6 represent edited templates, as opposed to the initial templates of FIG. 4.

20 The score for template 10 of FIG. 4 and the signal cipher of FIG. 3 would be eight, a complete match. The same score for edited template 10' of FIG. 6 rises to nine. Thus, the described method raises auto-correlation scores while lowering incorrect-recognition (cross-correlation) scores.

When one or more disjunct descriptors have been found and enhanced in a selected pair, the revised ciphers must be substituted for the originals before additional editing can proceed. Since a group edit operates upon interactions among all ciphers, they must constantly be updated. Following update, the group edit again seeks a highest-score pair. The process is repeated until all scores fall below a preset threshold, or no further improvement can be found. The template group edit is then over.

For clarity, score changes have been described in unit increments. Increments were assumed uniform among descriptors. A preferred embodiment employs higher increments, such as two or three, for corrective descriptors 25, 26 of FIG. 6. The higher scoring weights tend to increase auto-correlations and decrease cross-correlations more rapidly during an edit process. They also reduce the number of corrective descriptors required in revised templates.

During a recognition procedure, three options are available. If special scoring weights are not imposed, multiple corrective descriptors can be inserted, and treated by SCORE SELECTOR 21 of FIG. 1 in the manner of all other descriptors. Descriptor 25 of FIG. 6, for example, may be inserted several times. A second option is to identify corrective descriptors by insertion locations

imposed by GROUP EDIT 16 of FIG. 1, and have SELECTOR 21 assign appropriate scoring weights during the scoring process. As a third option, identifying or score-weighting symbols can be inserted by EDIT 16 into corrective descriptors. SELECTOR 21 can detect the symbols and adjust the score accordingly. Regardless of the option selected, appropriate scoring weights are applied and employed during a highest-score search by SELECTOR 21. A recognition is made when an input signal cipher has been compared to all edited templates by COMPARATOR 15 and SELECTOR 21 and has produced a highest score.

For simplicity of explanation, the number of cells, scores, and ciphers have been held to very low numbers. It is to be understood that in practice the numbers are often immensely greater.

Thus, while the invention has been particularly shown and described with reference to preferred embodiments thereof, it will be understood to those skilled in the arts that various changes in forms and details may be made therein without departing from the spirit and scope of the invention.

What is claimed as new and desired to be protected by Letters Patent is set forth in the appended claims: